

MAX-PLEX8S

ECONOMICAL 8 CHANNEL / 960H ANALOG DVR

ANALOG 960H



SPECIFICATIONS

*PLAYBACK	
Playback	8CH
Search	Time/calendar search, event (motion, external)
Smart Search	Apply different colors to display whether a channel in a period of time recording or not
Function	Play, Pause, FF, FB; Digital zoom
*NETWORK	
Interface	RJ45
Protocol	TCP/IP, UDP, DHCP, DNS, PPPOE, DDNS
Others	10 users online, dual stream
*ALARM	
Mode	Sensor, Motion, Video Loss
Output	1CH
Triggering	Record, PTZ move, e-mail, etc
*PORT	
HDD	SATA x 1, support 3T per HDD
RS485	RS485 x1, support PTZ and keyboard
USB	USB2.0 x 2, one for mouse, 1 for USB BU device
Remote Controller	Optional
*POWER / DIMENSIONS / WEIGHT	
Power	DC: 12V
Working Environment	0~50°C, 10%~90% (Humidity)°
Dimensions	300 x 270 x 58 (mm) 11.8"x 10.6 "x 2.3" (inches)
Weight	1.4(kg) 3 (pounds)
*SYSTEM	
Operating System	Embedded Linux
CPU	Cortex A9
Compression	Standard H.264
*VIDEO	
Input	BNC x 8
Output	BNC 1 - VGA x 1:1920x1080 -HDMI x 1:1920x1080
*AUDIO	
Input	RCA x 4
Output	RCA x 1
2-way audio	Take up 1CH audio input
*RECORD	
Resolution	960H/D1/CIF /960*576/704*576/352*288(PAL) 960*480/704*480/352*240(NTSC)
Frame Rate(fps)	00/200/200(PAL) /120/240/240(NTSC)
Bit Rate	128K~2Mbps
Encode	VBR/CBR
Quality	6 Level
Mode	Manual, Timer, Motion,sensor
Bit Rate	128K~2Mbps
*CELL PHONE	
OS	iPhone, Blackberry, Andriod, Windows phone
Function	Multi-screen surveillance(for certain model), snapshot, PTZ control, save the device list record

KEY BENEFITS

- HDMI OUTPUT FOR HIGH RES. DISPLAY
- SUPPORTS 960H REAL TIME RECORDING FOR EACH CHANNEL
- DUAL STREAMING TECHNOLOGY
- MULTI-USER ONLINE SIMULTANEOUSLY
- COMPLETE SDK SOFTWARE AVAILABLE
- 960H RESOLUTION

The PLEX8S is an economically priced 8-channel security DVR that uses H264 video compression for storing clear, sharp video surveillance files.

Multiplex operation allows you to perform more than one task at once. You can watch a recording that happened a day ago (or week, month, or more) without disturbing a scheduled recording or other operation. You can inspect the menu and alter settings without interfering with current surveillance operations (unless that is your intent). Watch recordings or make backups while monitoring your property at the same time, secure in the knowledge that unwanted activity won't slip by.



FRONT VIEW



BACK VIEW

ACCESSORIES INCLUDED



USB MOUSE



12V POWER SUPPLY



REMOTE CONTROL

